

C-Gate 3 Release Notes

C-BUS

Table of Contents

C-Gate 3.3.3	5
Released	5
What's New	5
Fixes	5
Known issues.....	5
C-Gate 3.3.2	6
Released	6
What's New	6
Fixes	6
Known issues.....	6
C-Gate 3.3.1	7
Released	7
What's New	7
Fixes	7
Known issues.....	7
C-Gate 3.3.0	8
Released	8
What's New	8
Fixes	8
Known issues.....	8
C-Gate 3.2.4	1
Released	1
What's New	1
Fixes	1
Known issues.....	1
C-Gate 3.2.3	2
Released	2
What's New	2
Fixes	2
Known issues.....	2
C-Gate 3.2.2	3
Released	3

What's New	3
Fixes	3
Known issues.....	3
C-Gate 3.2.0	4
Released	4
What's New	4
Folder Changes.....	4
Project Format Change	4
C-Bus DALI-2 Gateway.....	4
DIMDD4 / DIMDD8 Dimmers	4
Command API Changes	4
Installing on Linux	5
Prerequisites	5
Folder Structure	5
Clean Installation	5
Migrate Existing Installation	5
Known Issues.....	6
Other Fixes	6

C-Gate 3.3.3

Released

July 2024

What's New

Updates to C-Gate include:

C-Bus Key Input units

- Support firmware version 1.3.0 of C-Bus Key Input units (KEYB2A, KEYB4A, KEYB6A, KEYH1A, KEYH2A, KEYH3A, KEYH4A).

Home Controller

- Support firmware version 5.4.0 of Home Controller (SYSWSR2).

C-Bus Automation Controllers

- Support firmware version 1.18.0 of C-Bus Automation Controllers (SYS_SHAC, SYS_NAC, SYS_NAC2, SYS_AC2).

New applications data structure

- Introduce the data structure of Audio application and Media Transport applications.

Performance improvement

- Support cross pages parameters RECALL of C-Bus devices (DIMDD4, DIMDD8, KEYB2A, KEYB4A, KEYB6A, KEYH1A, KEYH2A, KEYH3A, KEYH4A).

Fixes

- Unable to set the group address of DALI Line A Object 0 (SYS_DAL2).
- The catalogue number of a network device is not updated after replacing the device in the same address (All C-Bus devices).

Known issues

None

C-Gate 3.3.2

Released

May 2024

What's New

Updates to C-Gate include:

C-Bus Automation Controllers

- Support firmware version 1.17.0 of C-Bus Automation Controllers (SYS_SHAC, SYS_NAC, SYS_NAC2, SYS_AC2).

C-Bus DALI-2 Gateway

- Support firmware version 1.8.0 of C-Bus DALI-2 Gateway (SYS_DAL2).

C-Bus Digital Dimmer

- Support reading group addresses of C-Bus 4 and 8 Channel Digital Dimmers during QSYNC command (DIMDD4, DIMDD8).

Fixes

- Incorrect device description of C-Bus Automation Controllers (SYS_NAC, SYS_SHAC).
- Incorrect default value of Standby Brightness indicator and incorrect default value of Feature Enable in Linked Widget for new Saturn and Saturn Zen wall plates (KEYB2A, KEYB4A, KEYB6A, KEYH1A, KEYH2A, KEYH3A, KEYH4A).
- The issue of reading and saving Dimming Curve Selection and Dimming Profile Selection of C-Bus 4 and 8 Channel Digital Dimmers (DIMDD4, DIMDD8).

Known issues

None

C-Gate 3.3.1

Released

April 2024

What's New

Support for New Saturn and Zen Key Input Units

- In this release, support has been added for the new Saturn and Zen key input units (KEYB2A, KEYB4A, KEYB6A, KEYH1A, KEYH2A, KEYH3A, KEYH4A).

Fixes

None

Known issues

None

C-Gate 3.3.0

Released

April 2024

What's New

Updates to C-Gate include:

C-Bus DALI-2 Gateway

- Additional Measurement and Error Reporting application parameters are now supported in this release (future client feature).

C-Bus Digital Dimmers

- The network burden property of the digital dimmer devices are now supported in the network calculator in this release.

Performance Improvement

- Support has been added for the extended range of C-Bus replies for both new input and output devices in this release.

Fixes

- Fixed an issue with setting the C-Bus power supply property for new output devices (future client feature).

Known issues

None

C-Gate 3.2.4

Released

February 2024

What's New

Updates to C-Gate include:

C-Bus Digital Dimmers

In this release, support has been added for the dimmer mode and override flags in SET Commands in the C-Bus Digital Dimmer device DIMDD4 (5504D2D) and DIMDD8 (5508D1D).

C-Bus Automation Controller and Application Controllers

In this release, support has been added for version 1.16.0 of the C-Bus Automation Controller and C-Bus Application controller. This applies to the following devices:

- SYS_SHAC (5500SHAC & LSS5500SHAC)
- SYS_NAC (5500NAC & LSS5500NAC)
- SYS_NAC2 (5500NAC2)
- SYS_AC2 (5500AC2)

Fixes

- Unexpected error when scanning C-Bus Universal Dimmer device (DIMDU4).
- Project conversion issues:
- Some projects appear with a “Failed” status (in C-Bus Commission and Toolkit), which may result from:
 - A conflict in the conversion process between project files
 - Importing a Toolkit backup project and proceeding to replace an existing project
 - XML files that are not actually project files (e.g. device template files)
 - Device template file is not being handled and incorrectly recognised as a normal project.
 - The conflict between the project XML files in backup folder and the XML file in Projects root folder, during Toolkit Project Restore operation.
 - Project not converted successfully is not reflected as Failed in PROJECT DIR command.
- When a project file is imported and replaced using Toolkit the XML project file shall not remain in the root project folder.
- Project XML files will be restore if a project conversion has failed.

Known issues

None

C-Gate 3.2.3

Released

January 2024

What's New

Updates to C-Gate include:

- Support firmware version 1.3.0 of DIMDD4 (5504D2D) and DIMDD8 (5508D1D) C-Bus Digital Dimmer devices.

Fixes

None

Known issues

- Incorrect project conversion status reflected in C-Bus Commission or Toolkit upon restart. *Workaround: Close all C-Bus commissioning clients (both C-Bus Commission software and Toolkit) and restart the application(s).*
- Some projects appear with a "Failed" status (in C-Bus Commission and Toolkit), which may result from:
 - A conflict in the conversion process between project files
 - Importing a Toolkit backup project and proceeding to replace an existing project
 - XML files that are not actually project files (e.g. device template files)

C-Gate 3.2.2

Released

November 2023

What's New

Updates to C-Gate include:

- Update C-Bus DALI-2 Gateway firmware version default to version 1.7.0.
- Device update to support C-Bus DALI-2 Gateway and DALI Device Primary Control Function.
- Added support for C-Bus Network Devices section firmware update notification.
- Fixed the transfer of new levels to a C-Bus Controller within existing groups (refer to SpaceLogic C-Bus Commission 2.0.1 – DALI-2 Gateway Hotfix release notes for full details).

Fixes

Project conversion in “Failed” or “Waiting” state.

- A data migration bug that may affect the conversion of some projects from XML to the new format is now resolved.

Known issues

- C-Gate may still be running after closing the software.
- After the installation is complete, C-Gate will start up automatically.

C-Gate 3.2.0

Released

October 2023

What's New

Folder Changes


This release changes where the C-Gate application and its project files are stored on disk.


C-Gate is now installed into C:\Program Files\Schneider Electric\C-Gate 3 by default.

Project files are stored in C:\Users\YourUserName\Documents\C-Bus Commission 2\Projects

Project Format Change

This release introduces a new database format for projects, replacing the old XML format.

 *This new project format is not editable outside of C-Gate and other associated C-Bus software.*

 *This new project format is not compatible with C-Gate 2 or below.*


Old format projects are converted by C-Gate automatically to the new format as a background task when C-Gate is started. Projects are converted according to their last modified date, meaning that the most recently used will be converted first. Projects waiting to be converted or in the process of conversion cannot be opened until they have been successfully converted.

After conversion, backups of the old format projects can be found in

C:\Users\YourUserName\Documents\C-Bus Commission 2\Projects\ProjectName\XML Backup Files

where

- *YourUserName* is the name of your user account
- *ProjectName* is the name of the C-Bus project that was converted

 *We strongly recommend creating a separate back up of projects before installing and running this release.*

C-Bus DALI-2 Gateway

This release adds support for the C-Bus DALI-2 Gateway (5502CDGP230) and DALI devices.

DIMDD4 / DIMDD8 Dimmers

This release adds support for the DIMDD4 (5504D2D) and DIMDD8 (5508D1D) dimmer devices.

Command API Changes


The PROJECT DIR command has been enhanced with a new optional parameter that includes additional information in the responses. If the parameter is not specified, then the responses are the same as in previous versions of the command.

There have been cybersecurity improvements to the command API.

Installing on Linux

Prerequisites

- A 64-bit Linux operating system
 - Linux installation testing was performed on Ubuntu 22.04.3
- The C-Gate 3.2 package (cgate-3.x.x_xxxx.zip)
- A 64-bit Java Runtime Environment (JRE)
 - JRE 1.8.0_202 is the recommended and supported version, which can be downloaded from the Oracle website

 *Currently only 64-bit Linux operating systems are supported for installation*

Folder Structure

The *application* folder is the folder where CGate.jar is located.

The *application data* folder is the folder where log and configuration files are stored. This location is defined by the CGATE_APPDATA environment variable.

The *home* folder is the folder where project files are stored. This location is defined by the CGATE_HOME environment variable.

Clean Installation

1. Install the JRE and ensure it is set as the default
2. Extract the C-Gate zip package into
 - /usr/local/bin/cgate3
3. Set the CGATE_HOME and CGATE_APPDATA variables as permanent environment variables as defined below. If these variables are not set, then C-Gate will attempt to write project, log and configuration files in the same folder as CGate.jar (in which case ensure that the user account used to start C-Gate has been granted read and write permissions to that location)
 - CGATE_HOME = /home/<username>/cgate3/home
 - CGATE_APPDATA = /home/<username>/cgate3/appdata
4. Create the folders below (corresponding to the environment variables)
 - /home/<username>/cgate3/home/Projects
 - /home/<username>/cgate3/appdata/config
5. Navigate to
 - /usr/local/bin/cgate3
6. Execute
 - java -jar cgate.jar

Migrate Existing Installation

- Make a backup of the C-Gate 2 folders.
 - Make a separate backup of the tag folder if the project XML files are not stored in the default folder C-Gate2\tag
- Follow steps 1 – 4 of the Clean Installation
- Copy files from the C-Gate 2 tag folder to the C-Gate 3 Projects folder
- Copy the CGateConfig.txt file from C-Gate 2 to C-Gate 3 (if needed)

- Follow steps 5 – 6 of the Clean Installation

Known Issues

- SLCC-1078: The DBNEW and DBSAVE commands are not working

Other Fixes

None